

INTERNATIONAL STANDARD

**ISO/IEC
15444-2**

First edition
2004-05-15

AMENDMENT 2
2006-01-01

Information technology — JPEG 2000 image coding system: Extensions

AMENDMENT 2: Extended capabilities
marker segment

*Technologies de l'information — Système de codage d'images
JPEG 2000: Extensions*

AMENDEMENT 2: Segment de marqueur à capacités étendues

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC 15444-2:2004/AMD2:2006

Reference number
ISO/IEC 15444-2:2004/Amd.2:2006(E)



© ISO/IEC 2006

PDF disclaimer

This PDF file may contain embedded typefaces. In accordance with Adobe's licensing policy, this file may be printed or viewed but shall not be edited unless the typefaces which are embedded are licensed to and installed on the computer performing the editing. In downloading this file, parties accept therein the responsibility of not infringing Adobe's licensing policy. The ISO Central Secretariat accepts no liability in this area.

Adobe is a trademark of Adobe Systems Incorporated.

Details of the software products used to create this PDF file can be found in the General Info relative to the file; the PDF-creation parameters were optimized for printing. Every care has been taken to ensure that the file is suitable for use by ISO member bodies. In the unlikely event that a problem relating to it is found, please inform the Central Secretariat at the address given below.

© ISO/IEC 2006

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Case postale 56 • CH-1211 Geneva 20
Tel. + 41 22 749 01 11
Fax + 41 22 749 09 47
E-mail copyright@iso.org
Web www.iso.org

Published in Switzerland

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of the joint technical committee is to prepare International Standards. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

Amendment 2 to ISO/IEC 15444-2:2005 was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 29, *Coding of audio, picture, multimedia and hypermedia information*, in collaboration with ITU-T. The identical text is published as ITU-T Rec.T.801/Amd.2.

Introduction

The JPEG 2000 specification is structured in several parts: Part 1 is defined in ITU-T Rec. T.800 | ISO/IEC 15444-1 ("Core coding system"). Part 2 is defined in ITU-T Rec. T.801 | ISO/IEC 15444-2 ("Extensions"). Part 3 is defined in ITU-T Rec. T.802 | ISO/IEC 15444-3 ("Motion JPEG 2000"). Part 4 is defined in ITU-T Rec. T.803 | ISO/IEC 15444-4 ("Conformance testing"). Part 5 is defined in ITU-T Rec. T.804 | ISO/IEC 15444-5 ("Reference software"). Part 6 is defined in ISO/IEC 15444-6 ("Compound image file format"). Part 7 has been withdrawn. Part 8 is defined in ISO/IEC 15444-8 ("Secured JPEG format"). Part 9 is defined in ITU-T Rec. T.808 | ISO/IEC 15444-9 ("Interactivity tools, APIs and protocols"). Part 10 is defined in ISO/IEC 15444-10 ("3-D and floating point data"). Part 11 is defined in ISO/IEC 15444-11 ("Wireless"). Part 12 is defined in ISO/IEC 15444-12 ("ISO base media file format").

The need for this amendment arises from a lack of sufficient codespace in the Rsiz capabilities parameter in the SIZ marker segment. The Rsiz parameter contains 16 bits, which are used to signal decoding capabilities required by the encoded codestream. According to Table A.10 of ITU-T Rec. T.800 | ISO/IEC 15444-1, the only values used in Part 1 codestreams are:

Rsiz = 0000 0000 0000 00xx

where:

- xx = 00 indicates a generic Part 1 codestream
- xx = 01 indicates a profile 0 codestream
- xx = 10 indicates a profile 1 codestream

In Table A.2, the first bit of Rsiz is used to indicate the presence of Part 2 features, and the bit values assigned to specific Part 2 capabilities are:

Rsiz = 1000 yzzz zzzz zzzz

where y = 1 indicates a codestream using Part 2 (precinct-dependent quantization) and bits 6-16 (the z-bits) indicate extensions defined in the Part 2 annexes. In particular, note that there are only 3 unused bits (bits #2, 3, and 4) remaining in the Rsiz field.

Signalling Part 2 capabilities requires a full bit per capability because Part 2 features can be selected independently (i.e., in arbitrary combinations) by encoders, and this situation can be expected to continue for extensions defined in subsequent Parts of the JPEG 2000 family or in future Part 2 amendments. This includes extensions presently under development in JPEG 2000 Parts 8 (JPSEC), 10 (JP3D), and 11 (JPWL), many of which will be used in conjunction with other extensions from different Parts of JPEG 2000. Consequently, the three remaining unused bits in Rsiz are far from sufficient for signalling future JPEG 2000 codestream capabilities.

Rather than forcing future JPEG 2000 extensions to invent their own methods of signalling required codestream capabilities, this amendment defines a unified, scalable, semantically flexible framework for capabilities signalling that can be used by all future JPEG 2000 Parts and amendments. Moreover, it is fully backwards-compatible with the present capabilities signalling employed in the Rsiz parameter. The key idea is to define a new variable-length Part 2 marker segment (the CAP marker segment) that indicates the Parts and the specific extended capabilities used to encode the codestream in question. Use of the CAP marker segment is indicated by the second-most-significant bit in the Rsiz parameter.

The second bit in the Rsiz parameter can also optionally be used to indicate that a CAP marker segment is used. To a baseline decoder, this will appear as the indication of an unknown capability, which generally prevents the decoder from further decoding the codestream.

INTERNATIONAL STANDARD
ITU-T RECOMMENDATION

Information technology – JPEG 2000 image coding system: Extensions

Amendment 2
Extended capabilities marker segment

1) Table A.2

In Table A.2:

- *replace all occurrences of “1000” in the four most significant bits of the index values with “1x00”;* and
- *add the following entries immediately preceding the entry describing variable DC offset capability:*

0100 0000 0000 00xx	Capabilities specified in ITU-T Rec. T.800 ISO/IEC 15444-1 and at least one extended capability indicated in the CAP marker segment
1100 xxxx xxxx xxxx	Extended capabilities defined in this Recommendation International Standard as indicated in this parameter, and at least one other extended capability indicated in the CAP marker segment

so that Table A.2 will now read:

Value (bits)	Capability
MSB	LSB
0000 0000 0000 0000	Capabilities specified in ITU-T Rec. T.800 ISO/IEC 15444-1 only
1x000 xxxx xxxx xxxx	At least one of the extended capabilities specified in this Recommendation International Standard is present
0100 0000 0000 00xx	<u>Capabilities specified in ITU-T Rec. T.800 ISO/IEC 15444-1 and at least one extended capability indicated in the CAP marker segment</u>
1100 xxxx xxxx xxxx	<u>Extended capabilities defined in this Recommendation International Standard as indicated in this parameter, and at least one other extended capability indicated in the CAP marker segment</u>
1x000 xxxx0 xxxx xxxx1	Variable DC offset capability is required to decode this codestream ^{a) b)}
1x000 xxxx xxxx xx1x	Variable scalar quantization capability is required to decode this codestream ^{a)}
1x000 xxxx xxxx x1xx	Trellis coded quantization capability is useful to decode this codestream ^{c)}
1x000 xxxx xxxx1 xxxx	Visual masking capability is useful to decode this codestream ^{c)}
1x000 xxxx xxxx1 xxxx	Single sample overlap capability is required to decode this codestream ^{a)}
1x000 xxxx xx1x xxxx	Arbitrary decomposition style capability is required to decode this codestream ^{a)}
1x000 xxxx x1xx xxxx	Arbitrary transformation kernel capability is required to decode this codestream ^{a)}
1x000 xxxx1 xxxx xxxx	Whole sample symmetric transformation kernel capability is required to decode this codestream ^{a)}
1x000 xxxx1 xxxx xxxx	Multiple component transformation capability is required to decode this codestream ^{a)}
1x000 xx1x xxxx xxxx	Non-linear point transformation capability is useful to decode this codestream ^{c)}
1x000 x1xx xxxx xxxx	Arbitrary shaped region of interest capability is required to decode this codestream ^{a)}
1x000 1xxx xxxx xxxx	Precinct-dependent quantization is required to decode this codestream ^{a)}
	All other values reserved

^{a)} "Required to decode" implies that no useful data or image can be reconstructed without the use of this capability.

^{b)} Shall not be used with the multiple component transformation.

^{c)} "Useful to decode" implies that use of this capability would improve the quality of the reconstructed data or image; however, the data or image may be decoded without its use.

2) New clause A.3.13

Add the following A.3.13:

A.3.13 Extended capabilities (CAP)

Function: Signals that extended capabilities were used to create (and are recommended or required to decode) a codestream.

Usage: Optional. If present, must be included anywhere in the main header after the SIZ marker segment. The second-most-significant bit in Rsiz may optionally be set to 1 to indicate the presence of the CAP marker segment.

Length: Variable.




Figure A.13 – Extended capabilities syntax

CAP: Marker code. Table A.49 shows the size and values of the symbol and parameters for the extended capabilities marker segment.

Lcap: Length of the CAP marker segment (not including the marker). Length is given by the following formula:

$$\text{Lcap} = 6 + 2n \text{ bytes}$$

where n is the number of 1-bits occurring in Pcap.

Pcap: 32-bit field indicating the Parts containing extended capabilities that are used to encode the image. A value of 1 in the k th-most-significant bit of Pcap indicates the use of capabilities from Part k (ISO/IEC 15444- k). The first non-zero bit in Pcap corresponds to the first Ccap ^{i} field ($i = 1$); the second non-zero bit in Pcap corresponds to the second Ccap ^{i} field ($i = 2$), etc. Table A.50 shows the usage of the Pcap parameter.

Ccap ^{i} : 16-bit field indicating capabilities specified in Part p_i where bit $\#p_i$ is the i th non-zero bit in Pcap. If $p_1 = 2$, the bits in Ccap ^{i} shall indicate capabilities defined in Part 2 amendments; the MSB of Rsiz may be set to the value 1 in this case. For other Parts, the bits in Ccap ^{i} may be used to indicate capabilities defined in Part p_i . The precise meaning of the bits in Ccap ^{i} shall be specified in Part p_i (ISO/IEC 15444- p_i).

Table A.49 – Extended capabilities parameter values

Parameter	Size (bits)	Value
CAP	16	0xFF50
Lcap	16	80-560
Pcap	32	See Table A.50
Ccap ^{i}	16	Value and meaning specified in ISO/IEC 15444- k , where the i th non-zero bit in Pcap occurs in its k th most significant bit

Table A.50 – Part parameter values for the Pcap parameter

MSB Values (bits)	LSB	Part parameter
1xxxx xxxx xxxx xxxx xxxx xxxx xxxx xxxx		Extended capabilities from ISO/IEC 15444-1 were used to encode the image
x1xx xxxx xxxx xxxx xxxx xxxx xxxx xxxx		Extended capabilities from ISO/IEC 15444-2 were used to encode the image
...		...
xxxx xxxx xxxx xxxx xxxx xxxx xxxx xxxx1		Extended capabilities from ISO/IEC 15444-32 were used to encode the image